### DSR ProSeries 12V /24V Jump Starter

## 4400 Peak Amps | 750/475 Cranking Amps | 525/350 Cold Cranking Amps

A new offering in Schumacher's ProSeries jump starter line, the DSR115 offers powerful performance for both 12V and 24V batteries, providing 750 cranking amps and 525 cold cranking amps. New case design, metal clamps and improved, high-output AGM batteries set this unit apart from the competition. Solid performance, design and long-lasting durability make the DSR115 a great choice for professionals.

- (2) High-output AGM battery for 12V / 24V systems
- 4400 Peak Amps | 750/475 Cranking Amps | 525/350 Cold Cranking Amps
- 2 AWG, 60" cables
- 2A automatic external charger for quick recharging without worry of overcharging.
- **Digital Display** displays internal battery percent of charge
- Rust and corrosion-proof case with protective side caps
- Use in vertical or horizontal position
- 12-Volt DC Power Outlet –to power 12 volt devices and recharge unit while driving (Male-to-male in-vehicle charging cord included.)
- USB port for powering or recharging portable electronic devices.
- Unique Red On/Off power switch helps prevent accidental sparking
- Smart Eco Energy meets the highest industry standards for energy efficiency
- Reverse connection warning

# 1 Year Limited Warranty

#### Contents

(1) DSR115 jump starter (1) 2A automatic external charger (1) 12V DC charging cable (1) Manual

## Specifications

Internal battery type: Maintenance-free AGM lead-acid

Nominal voltage: 12V/24V DC

Capacity: 2 x 22 Ah

DC power outlet (max. continuous load): 15A

Peak amps: 4400

Cranking amps: 750/525 Cold cranking amps: 475/350 Jumper cables: 2 AWG, 60"

Charger input voltage: 120V AC @ 60Hz, 0.5A

Charger output voltage: 12V

Charger output current rating: 2A @ 12V

Sell Countries: USA/Canada